


1.Specifications RX-Multi



2.Technical Parameters

- 1.The RX-Multi can be worked at the input AC/DC 9V~30V.
- 2.Channel : CH1\CH2 ,The default output is NO; If you need to output NC,please open the product shell and select Jump Cap "COM-NC".

3.Brand selector

With 8 bits dip switch,the user can make difference combination for different remote brands.The brands selection show as table 1.

4.Learn Button and LED

In RX-Multi receiver, Learning button S1 \ S2, indicator light L1\ L2.

5.Operate How to entry remote and Erase all remote

Learn the remote control:

Step1. Selecting the correct brands for remote will be entry by dip switch;

Step2. Press the learn button, the LED turn on. Press the button on the remote, the LED flashes, this button entry into the RX Multi successfully. (Repeat step 2 for another button)

Tips:2 channels works at same.

Clear all remotes control data:

Pressing and holding either learn button , the LED lights up. Keep hold and press this button until the LED turn off. All data in the memory card will be erased permanently.

Notice:Be carefully for erasing all data in the memory card. The data will be erased permanently and cannot be recovered.

Item	Selection Dipswitch	Marcas Brands	Frec.
1		NICE FLORS FLO1-RS, FLO2-RS, FLO2R-SC FLO4-SC, FLO1R-M, FLO2R-M, FLO4R-M NICE MODEL: ON1, ON2, ON4, ON9 ON1E, ON2E, ON4E, ON9E NICE Era-Inti	ASK 433.92MHz
2		MARANC MODELS: Digital 222	ASK 433.92MHz
3		MARANTEC	ASK 868.35MHz
4		FAAC SLH Rolling Code MODELS: XT2 433 SLH	FSK 433.92MHz
5		FAAC (Genuine Only) MODELS: XT4 868 SLH LR\SPA 78009	FSK 868.8MHz
6		Liftmaster Security+ MODELS: 371LM	ASK 315MHz
7		Liftmaster Security+ MODELS: 971LM	ASK 390MHz
8		Liftmaster	ASK 868MHz
9		Universal rolling code GLID EROL-TM305C	ASK 315MHz

10		Rolling code: Aprimatic , APOLLO ALLMATIC-TECH3 , B.RO , FOR4 BFT-MITTO , B RCB , FAAC XT4RC Beninca , Dtm , Doorhan , Fox GIBIDI , GENius , NiceSmilo Pujol , PTX4 AVA ,ROSSI , Sotex	ASK 433.92MHz
11		Universal fixed code	ASK 300MHz
12		Universal fixed code	ASK 310MHz
13		Fixed code Ditec , V2	ASK 315MHz
14		Universal fixed code MODELS: GTO	ASK 318MHz
15		Fixed code	ASK 330MHz
16		Universal fixed code Ditec , V2	ASK 390MHz
17		Fixed code Be Happy S2 , BFT-TEO , CAME Ditec-GOL4C , BIXP2 , FAAC-TM433 Key , Kingates , Motorline , Poteco SERAI , SEA-SMART DUAL433MHz V2-S.P.A PHOX2 433 , PHOENIX2 Roger-M80 TX44R, R80 TX104R, H80 TX22 TOK Mini-PPA	ASK 433.92MHz
18		Merlin M832	FSK 433.92MHz

19		Hormann-HSM4-868 Bernier V2-S.P.A PHOX4-868 SEA-S.r.l	868MHz
20		Prastel	ASK 433.92MHz
21		Sommer MODELS: TX03-868-4 , TX02-868-2	FSK 868.8MHz
22		Sommer MODELS: TX03-434-4-XP	FSK 434.4MHz
23		Clemsa Mastercode	ASK 433.92MHz
24		JMC TECH	ASK 868.35MHz
25		ROJAYEN	ASK 868.35MHz
26		ATA PTX5 PTX-5 V1 TrioCode/Tricode B&D PTX5 PTX-5 Tritran TriTran B&D Tritran	ASK 433.92MHz
27		Merlin+ MODELS: C945	ASK 433.92MHz