

REMOTE PRO

PROGRAMMING INSTRUCTIONS



FADINI CLONING

CLONING THE FADINI DIVO 71 TO YOUR WORKING FADINI REMOTE

This remote is pre-configured to Fadini Astro by the manufacturer. You can check the current mode by pressing and holding the bottom two buttons until the red LED flashes:

- 1 Flash = Astro 43
- 3 Flashes = Jubi 433

To switch from Fadini Astro to Fadini Jubi, follow these steps:

1. Press and hold the top right and bottom right buttons (buttons 1 and 4) simultaneously for 5 seconds.
2. The remote will flash to confirm the mode change:
 - 1 Flash = Astro 43
 - 3 Flashes = Jubi 433

Place your working Fadini remote and the new Fadini Divo remote within 5 cm of each other.

1. Press and hold the top left button on the Divo, then press the top right button twice while holding.
2. Release the top left button – the remote will flash 3 times to confirm it's in learn mode.

Note: The Divo will have a steady LED light during learn mode.

3. Press and hold a working button on the old remote. The Divo will flash 3 times to confirm the signal is received.

WARNING

This product may contain a coin/button cell battery. Keep product and batteries away from children. A battery can cause severe or fatal injuries in 2 hours or less if swallowed or placed inside any part of the body. Seek immediate medical attention if it is suspected that a coin/button cell battery has been swallowed or placed inside of any part of the body.

